

# INDEPENDENT PORTABLE ELECTRIC POWER TOOL AUTOPRESS 55



## **PRACTICAL**

This independent portable electric power tool crimps connectors from 4 to 150 mm<sup>2</sup> for industrial installations and distribution lines thanks to the diverse interchangeable dies (4E... and 5E...). The head pivots through 180° allowing the tool to always be held in the optimum position.

## **EASY TO USE**

- light (< 3,2 kg)
- compact
- one-handed control

## **POWERFUL / EFFECTIVE**

The 12V rechargeable battery gives an independent working capacity of more than 80 crimps on the biggest cables. As an option, a battery with a LED indicator shows how much independent capacity is left.

## **SAFE**

A safety valve which gives an audible click indicates when the crimp is complete. The electronic variator in the trigger gives complete control over the positioning of the tool.

## **GUARANTEE**

1 year.

## Independent portable electric power tool AUTOPRESS 55




AUTOPRESS 55 complete outfit  
(box including one tool with battery n° 018098  
and one charger n° 018099)  
AMP-SIMEL code: 018096 • AMP ref.: 719412-1

### CHARACTERISTICS

|  |  |
|--|--|
| For crimping connectors<br>from 4 to 150 mm <sup>2</sup> . | Automatic release<br>with audible "click"<br>when crimp is complete. |
| Power: 55 kN.  | Piston return by means<br>of release lever.                          |
| Capacity: Ø 26 max.  | Head rotating through 180°<br>with quick-action<br>open and close.   |
| Weight: 3.2 kg.  | Interchangeable dies.  |
| Stroke of piston: > 11 mm.                                 |  |
| Hydraulic system<br>with speed variator.                   |  |

### PRESENTATION

AMP-SIMEL offers this new hydraulic electric tool  
with various options as shown on the right. The product  
includes a wrist-strap to insure good grip on the tool  
and a hanging ring for users working in suspension harness.  
The easily interchangeable dies  
(references 4E..., 5E..., 4P..., 4M... and 4R)  
allow for hexagonal crimping or re-rounding and are sold  
upon request.



Empty box AUTOPRESS 55  
AMP-SIMEL code: 018097  
AMP ref.: 719413-1



Battery AUTOPRESS 55 without LED  
12V 2000 mAh  
AMP-SIMEL code: 018098  
AMP ref.: 719414-1



Battery AUTOPRESS 55 with LED  
12V 2000 mAh  
AMP-SIMEL code: 018559  
AMP ref.: 719828-1



AUTOPRESS 55 speed charger  
15 minutes  
AMP-SIMEL code: 018103  
AMP ref.: 719416-1



AUTOPRESS 55 charger  
1 hour  
AMP-SIMEL code: 018099  
AMP ref.: 719415-1

\*LED = Light Emittive Diode.

## References of usable dies

| Copper connectors |        |          | Overhead cable connectors |        |          | Re-rounding |        |          |
|-------------------|--------|----------|---------------------------|--------|----------|-------------|--------|----------|
| Ref.              | Code   | AMP ref. | Ref.                      | Code   | AMP ref. | Ref.        | Code   | AMP ref. |
| 4E120.4 Cu        | 039730 | 708802-1 | 4E100 E54                 | 040660 | 708806-1 | 4R50        | 042600 | 708743-1 |
| 4E35.6 Cu         | 039690 | 708797-1 | 4E120 E68                 | 040670 | 708807-1 | 4R70        | 042610 | 708742-1 |
| 4E50.10 Cu        | 039700 | 708798-1 | 4E140 E83                 | 039750 | 708810-1 | 4R95        | 042620 | 708741-1 |
| 4E60 Cu           | 018470 | 708800-1 | 4E72                      | 042990 | 708805-1 | 4R120       | 042630 | 708740-1 |
| 4E70.16 Cu        | 039710 | 708799-1 | 4E173                     | 039740 | 708809-1 | 4R150       | 031870 | 708739-1 |
| 4E95.25 Cu        | 039720 | 708801-1 | 4E173/5                   | 047160 | 708808-1 |             |        |          |
| 5E150 Cu          | 036050 | 708811-1 | 5E215                     | 026740 | 708664-1 |             |        |          |
| 4M AMP/III 10     |        | 1018532  |                           |        |          |             |        |          |
| 4M AMP/III 16     |        | 1018533  |                           |        |          |             |        |          |
| 4M AMP/III 25     |        | 1018534  |                           |        |          |             |        |          |
| 4M AMP/III 35     |        | 1018535  |                           |        |          |             |        |          |
| 4P AMP/III 10-16  |        | 1018536  |                           |        |          |             |        |          |
| 4P AMP/III 25-35  |        | 1018537  |                           |        |          |             |        |          |